



Optus Mobile Technical Support Centre
Phone: 1300 307 937 Mon-Sun 24Hrs



Motorola V3 Optus Zoo

GPRS GUIDE

Introduction

Please note that this guide is not intended as a definitive or exhaustive technical manual. This guide has been deemed appropriate to be sent to you based on the symptoms that you have described. If you have any further queries or concerns, please do not hesitate to contact Optus on 1300307937.

This Guide outlines the steps to follow to setup a Motorola V3 for use with Optus Zoo via GPRS. This phone comes preprovisioned with WAP.

Activating Pre-provisioned Settings	Press the Menu button, scroll to Web Access , press Select Scroll to Web Sessions , press Select Highlight Optus Zoo , press the Menu button, select Set Default Highlight Optus Zoo , press Launch
Entering Manual Settings	Press the Menu button, scroll to Web Access , press Select Scroll to Web Sessions , press Select Scroll to New Entry , press Select Highlight Name , press Change and enter Optus Zoo , press OK Highlight Homepage , press Change , enter http://networker.optus.net.au/wap/index.wml , press OK Scroll to Service Type 1 , press Change , select WAP Highlight Port 1 , press Change , enter 9201 , press OK Highlight Service Type 2 , press Change , select WAP Highlight Port 2 , press Change , enter 9201 , press OK Highlight Timeout , press Change and select 2 Highlight Speed (Bps) 1 , press Change , select 9600

	<p>Highlight Line Type 1, press Change, select ISDN</p> <p>Highlight Speed (Bps) 2, press Change, select 9600</p> <p>Highlight Line Type 2, press Change, select ISDN</p> <p>Highlight GPRS APN, press Change, enter wap.optus.net.au or prepaidyesoptus, press OK</p> <p>Press Done</p> <p>Highlight Optus Zoo, press Launch</p>
--	--